



Lighting Your Life Since 1970

Product Specifications - 87883SV

Job Name:	Job Type:
Quantity:	Comments:



**87883SV**

**CounterMax MX-LD 3-Light LED Kit**

Uses MXInterLink2 accessories. Click [here](#) for a complete list of compatible accessories.

**Finish**  
Silver

**Glass/Shade**

**Product Category**  
Under Cabinet Disc

**Lamping**

Number of Bulbs	72
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	.07
Max Fixture Wattage	5.1
Rated Life	±40,000 Hours
Rated Lumens	±390
Color Temp	±3,500 K
Bulb(s)	Integrated
Light Up/Down	N/A
Beam Spread	120
CRI	70-75
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	No

**Measurements**

Width	
Height	
Length	N/A
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	0.00"
Max Overall Height	N/A
Hanging Weight	0.60 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

**Shipping**

Carton Weight	0.68 lbs
Carton Width	6"
Carton Height	2"
Carton Length	10"
Carton Cubic Feet	0.07
Master Pack	12
Master Pack Weight	9.26 lbs
Master Pack Width	12.00"
Master Pack Height	7.87"
Master Pack Length	20.47"
Master Cubic Feet	1.12
UPS Shippable	Yes

**Certification**

Safety Rating	Dry
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No
Dark Sky	N/A

**Other**

UPC Code	783209064461
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	Polycarbonate

**Equivalents**

Incandescent Watts	35.45
Fluorescent Watts	7.8

Maxim Lighting International and all designs, logos and images © 2015 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.