

Lighting Your Life Since 1970

Product Specifications - 87883WT			
Job Name:	ame: Job Type:		
Quantity:	Comments		



87883WT

CounterMax MX-LD 3-Light LED Kit

Uses MXInterLink2 accessories. Click here for a complete list of compatible accessories.

Finish White

Lamping

Number of Bulbs	72
Light Type	LED
Bulb Type	LED
Max Bulb Wattage	.07
Max Fixture Wattage	5.1
Rated Life	±30,000 Hours
Rated Lumens	±390
Color Temp	±3,500 K
Bulb(s)	Integrated
Light Up/Down	N/A
Beam Spread	120
CRI	70-75
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	No

-		10			
721	ass	/51	ho	\sim	e
91	ass	/ JI	Ia	w	

М			

Width	
Height	
Length	N/A
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
НСО	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	0.6 lbs
rianging weight	0.0 105
Height Adjustable	N/A
Height Adjustable	N/A
Height Adjustable Slope	N/A N/A
Height Adjustable Slope Chain Length	N/A N/A N/A
Height Adjustable Slope Chain Length Wire Length	N/A N/A N/A N/A

Product Category

Under Cabinet Disc

Shipping

Carton Weight	0.6 lbs
Carton Width	6"
Carton Height	2"
Carton Length	10"
Carton Cubic Feet	0.07
Master Pack	12
Master Pack Weight	9.3 lbs
Master Pack Width	12.0"
Master Pack Height	7.9"
Master Pack Length	20.5"
Master Cubic Feet	1.12
UPS Shippable	Yes

Certification

Other Dry UPC Code 783209064478 **Safety Rating Energy Star** Shades Included No CA Title 24 Crystals Included No CA Title 20 No Diffuser Included **ADA** Conversion Kit No Dark Sky N/A Material Polycarbonate

Equivalents

N/A

N/A

N/A

N/A

Incandescent Watts	35.45
Fluorescent Watts	7.8

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.